



## Custom Channels LCD Music Player How To Set Static IP

Your Custom Channels LCD Music player can be configured with a static internal IP address through the front panel menu buttons. Before you start you will need to know the IP configuration info:

- Desired static IP of the player
- Network's subnet mask
- Network's gateway IP address
- DNS address. We recommend using public DNS 8.8.8.8 and 8.8.4.4

Next, follow these steps to enter the information into the Custom Channels LCD music player:

1. With the player powered off enter the setup menu by pressing the "Esc" and "OK" buttons at the same time.
2. Display should read "Setup". Press OK.
3. Press the down arrow to display "Network Setup" then press "OK". The display should read "DHCP".
4. Press the down arrow once until the display shows "Static IP", the press "OK".
5. At the display "IP-Address: [OK] to edit" press "OK".
6. Enter the desired IP address of the player. Use the up/down arrows to select the correct number; use the right/left arrows to advance to the next or previous number. **NOTE:** IP addresses must be entered with leading zeros if necessary. 192.168.1.2 should be entered as 192.168.001.002.
7. After you have entered the IP address, press "OK" to go to the Network Mask menu.
8. Repeat steps 6 and 7 for each of Network Mask, Default Gateway, DNS 1 and DNS 2.
9. After entering DNS 2, the display will read "Ready", then press [OK] ([ESC] = again). Press "OK" to finish.
10. The display should read: "Network Setup". Press the [Esc] button twice and the player will turn itself off.
11. Press the power button to turn on and connect to the network.

### Questions?

Email [support@customchannels.net](mailto:support@customchannels.net) or call 303.444.7700 x7